



 **Cavi TV-SAT gas injected 75 ohm**
 75 ohm TV-SAT gas injected cables


 Cables TV-SAT gas injected 75 ohm

 Cables TV-SAT gas injected 75 ohm


 Cavo 75 ohm a bassa perdita e doppia schermatura

 75 ohm high screen low loss cable

 Cable 75 ohm à bas perte et haute schermature

 Cable 75 ohm baja perdita y alta schermatura


CAVOSAT1-3-4


**CAVOTE4I (ignifugo)**  
 (fireproof)  
 (ignifuge)  
 (ignifugo)


CAVOCO22AF



CAVORG213

MODELLO  
CODICE
**CAVOSAT1**  
**6199**
**CAVOTE3**  
**6201**
**CAVOSAT4**  
**6543**
**CAVOTE4I**  
**6856**
**CAVOCO22AF**  
**6218**
**CAVORG213**  
**6216**

MODELLO CODICE	CAVOSAT1 6199	CAVOTE3 6201	CAVOSAT4 6543	CAVOTE4I 6856	CAVOCO22AF 6218	CAVORG213 6216
<b>DIAMETRO</b> DIAMETER	6,7mm	6,7mm	6,7mm	6,8mm IGNIFUGO	10mm ANTIFIAMMA	11mm
<b>PESO</b> WEIGHT	27,5 Kg/m	31 Kg/m	40 Kg/Km	40 Kg/Km	130 Kg/Km	151,3 Kg/Km
<b>CAPACITA'</b> CAPACITY	52pF/m	52 pF/m			78 pF/m	101 pF/m
<b>DIELETRICO</b> DIELECTRIC	GAS INJECTED PEE / DG	GAS INJECTED PEE / DG			PEE	PE
<b>NASTRO</b> SCREEN-FOIL		Al - PET - Al			ALP	PVCII
<b>CONFORMITA'</b> CONFORMITY	EN 50117-5	EN 50117-5			EN 50117-5 ROHS CEI20-35 CEI20-22	MIL-C-17
<b>TRECCIA</b> SCREEN	Cu St 40%	Cu St 45%			Cu St 97%	Cu St 96%
<b>PERDITE</b> LOSSES	800MHz 25,5dB/100m 1000MHz 28,5dB/100m 1750MHz 38,9dB/100m 2050MHz 42,3dB/100m	800MHz 17dB/100m 1000MHz 19,4dB/100m 1750MHz 26dB/100m 2050MHz 28,3dB/100m			400MHz 10dB/100m 1000MHz 16dB/100m 2000MHz 21dB/100m 2500MHz 24dB/100m	700MHz 21dB/100m 9000MHz 24,9dB/100m 1000MHz 26dB/100m 4000MHz 70dB/100m
<b>IMPEDENZA</b> IMPEDENCE	75ohm	75ohm			50ohm	50ohm
<b>RAGGIO CURV.</b> CURVAT. RADIUS	25/50mm	35/70mm	35mm		75mm	50/100mm

**Accessori per il montaggio dei centralini e cavi coassiali intestati 75 ohm**

Accessories for mounting head-end CATV centrals and 75 ohm connected cables

Accessoires et cable coaxiales abouté 75 ohm pour le montage du centrales

Acésorios por el montaje de centrales y cables coaxiales intestados 75 ohm



Cavi coassiali e accessori

Coaxial cables and accessories

Cable coaxiales et accessoires

Cables coaxiales y acésorios

CF95-RAP



PN150



PN300



PF3



CCP



CCPL




**NEW**

CFP



PF5



RC-INS



**Cavi coassiali intestati - Coaxial cables with connectors - Cable coaxial avec connecteurs - Cable coaxiales con conectores**

MODELLO	PN150	PN300	PN450	PN600	PN750	PN900	PN1200	PN1500	PN2000
CODICE	5545	5046	5047	5048	5049	5050	5147	5148	5151

<b>CONNETTORI</b> CONNECTORS	IEC 9,5mm MASCHIO - MASCHIO (male-male)								
<b>LUNGHEZZA</b> LENGHT	150mm	300mm	450mm	600mm	750mm	900mm	1200mm	1500mm	2000mm
<b>CAVO</b> CABLE	RG59 75ohm NERO ( black ) Ø 5mm								

**Connettori e ponticelli - Connectors and bridge coaxials - Connecteurs et pont coaxials - Conectores y puente coaxiales**

MODELLO	CM95-RAP	CF95-RAP	CCP	CCPL	CCPA	SCFA	CFP
CODICE	6880	6881	5006	6809	5014	5112	6883

<b>TIPO</b> TYPE	CONNETT. MASCHIO	CONNETT. FEMMINA	PONTIC. BRIDGE CON.	PONTIC. BRIDGE CON.	PONT.AMP. AMP. BRIDGE CON.	FEMM. 9,5mm	CONN. "F" BRIDGE CON.
<b>CARATTERISTICHE</b> CHARACTERISTICS	RAP A VITE	RAP A VITE	P.33mm	P.35,5mm	P.33mm	90°CROM.	38,58mm

**Accessori vari - Accessories - Accessoires - Acesoios**

MODELLO	CPT	CPT12	CPTF12	PRT6	RVG	PF5	PF3	PF1	RC-INS
CODICE	5004	5005	6545	5894	5681	6582	6640	5059	6786

<b>TIPO</b> TYPE	INS.cc SU RF	TRANS.RF 24-12Vcc	TRANS.RF 24-12Vcc	MOSETT.	VENTIL. SALV.	PIASTRA	BARRA	PIASTRA	INSERTORE di TENSIONE
<b>CARATTERISTICHE</b> CHARACTERISTICS	IEC 9,5mm M/F	IEC 9,5mm M/F	"F" M/F	7 CAVI	230 Vac	FILTRI	DIN	FISS.	-